

MUSCLE STIMULATOR WITH TENS

VERTEX : N 535 – Computerised Muscle Stimulator with TENS

FEATURES :

- Highly user-friendly Control Panel
- Universal & Economical Unit
- Easy-to-operate design
- SDC Facility available
- Five types of Currents (Galvanic, Interrupted Galvanic, Faradic, Surge Faradic & TENS)



INPUT SUPPLY : 230 V AC, 50Hz
SIZE : L 11.5" x W 8" x H 4.5"
WEIGHT : 2.3 Kg. Approx

TECHNICAL SPECIFICATIONS :

Input Current : 58 mA
Output Current : 60 mA
Galvanic Output : Low ripple D.C. continuous adjustable from 0 to 145 volts

Interrupted Galvanic

Frequency : 1, 2, 3, 5, 10, 30, 50, 60, 100 Hz
Pulse Width : 0.01, 0.03, .10, .30, .40, 1, 3, 10, 30, 100, 300 Milli Seconds
Faradic : 1 Milli Second pulsed width and 60 Hz Frequency. Amplitude continuously adjustable from 0 to 145 volts

Surge Faradic

Contraction Period : Contraction period adjustable from 1 to 9 seconds
Rest Period : Rest period adjustable from 1 to 9 seconds
TENS : Pulse width 400 micro sec. & frequency 50 Hz

STANDARD ACCESSORIES :

- One pair plate electrode
- One pair Velcro Straps
- One point electrode

Note: As our products undergo continuous R&D for improvement, we reserve the right to change their specifications.